

INSTRUCTION SHEET

CLASS 2 TRANSFORMERS

1. Disconnect power supply before beginning installation to prevent electrical shock.
2. Select mounting location and type of mount and mount transformer.
 - A. Foot Mount: Use screws or bolts through holes in mounting foot. Transformer can be mounted in any position.
 - B. Multi mount: Can be mounted to plate or junction box, or can be foot mounted.
3. Determine the proper primary voltage. Refer to the following chart to select the proper wires.

<u>Primary Voltage</u>	<u>Lead Colors</u>
120 Volts	White & Black
208 Volts	White & Red
240 Volts	White & Orange
480 Volts	White & Blue

4. Connect secondary (output) connection.
 - On wire type transformers, be sure to insulate connection to avoid a possible short.
 - On terminal type transformers, be sure that no exposed wire can come in contact with any terminal.
 - On multi-output models, use the following chart to determine secondary voltage.

Red & Green	24 volts
Red & White	12 volts
Orange & White	2.5 volts

5. Insulate all unused wire(s) to prevent possible short.

6. Reconnect power supply and check all connections for proper operation.