










20135-E | Wireless Motion Detector

The 20135 Wireless motion detector transmitter effectively monitors indoor areas for human signature movements, which reduce false alarms. The device is fully supervised, includes a lithium battery, and case tamper protection. When activated the transmitter sends an alarm to the Crisis Controller® software showing the location of the alarm.



Features & Benefits

-  Compatible with the PALS® 9000 systems and Crisis Controller® Software
-  Wireless four-element passive infrared intrusion detector for use in ceiling mount applications
-  Full transmitter supervision includes alarms for low battery, tamper, and inactivity
-  Returns accurate RF location
-  Equipped with a special lens that offers wide coverage patterns, even at low mounting heights
-  Highly sensitive to moving heat infrared radiation
-  Increased immunity to radio interference, vibration, static, lightning, ambient temperature changes, and other causes of false alarms
-  Intelligent sleep timer extends battery life in high traffic environments
-  Detection range of 65 feet (20m)

Specifications

DIMENSIONS

4.5" x 2.5" x 1.6"

FREQUENCY

900 MHz

BATTERY

Included

BATTERY LIFE

2 Years

SLEEP TIME

90 seconds

*Battery Life when deployed will vary as a function of duty time used, frequency of alarm transmissions sent, LED brightness/frequency, location broadcast interval settings and environmental conditions at your site. Based upon 240mAh CR 2032 (Energizer). Ask your Actall Sales Representative for more details.



Accurate Location



24/7 Support



Affordable System



Optimize Workflow



Improve Safety



Valuable Data

