








91902 | Page Alert 5 Watt Page Tag

The 91902 Page Alert 5 Watt Page Transmitter is a hardware upgrade that allows immediate alarm notification to security or emergency care personnel. Combined with the PALS® 90149 Motorola Advisor Gold Pager and the PALS® 9000 system, help can be summoned with just the push of a button. The Page alert sends a full alphanumeric stream of data informing the paging recipient of the exact location and condition of the emergency.



Features & Benefits

-  Compatible with all Actall Corporation PALS systems
-  Quick and Easy Installation
-  Small and Compact
-  Communicates with the computer at 9600 baud
-  POCSAG 1200 Compatible
-  Available with high gain output antenna for extended range
(comes standard with rubber duck antenna)
-  Paging frequencies available on FCC Shared Use Frequency Program where no license is required

Specifications

| |
|---|
| DIMENSIONS |
| Dimensions: HxWxD 7.25" x 6.25" x 2.25" |
| OPERATING CURRENT |
| 1.2 Amps |
| WEIGHT |
| 1.5 lbs |
| OPERATING TEMPERATURE |
| 40° to 85° Centigrade |
| FREQUENCY |
| 460-470 (user specified) |
| RATED POWER |
| 5 Watts |
| OPERATING VOLTAGE |
| 9 VDC |

